Output Ratings

Generating Set Model	GEMCO150	GEMCO165S
380-415V, 50 Hz	150.0 kVA 120.0 kW	165.0 kVA 132.0 kW

Ratings at 0.8 power factor

Ratings Definitions

Prime Power - Model GEMCO 150

These ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hour.

Standby Power- Model GEMCO 165S

These ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No Overload is permitted on these ratings. The alternator on this model is peak continuous rated (as defined in (ISO 8528-3).

Technical Data

Engine Make & Model:	Perkins 1006TAG2
Alternator	Alternator of UK origin
Number of Cylinder/Alignment:	6 / In Line
Displacement: litres (cu.in)	6.0 (365.5)
Bore/Stroke: mm (in)	100.0 (3.9)/127.0 (5.0)
Compression Ratio:	17.0:1
Induction:	Turbocharged Air to Air Charge Cooled
Frequency:	50 Hz
Engine Speed:	1500 RPM
Gross Engine Power: kW (hp)	150.7 (202.0)
BMEP: kPa (psi)	2015.0 (292.2)
Piston Speed: m/sec (ft/sec)	6.4 (20.8)
Fuel Tank Capacity: litres (US qal)	300 (79.3)
Fuel Consump, 150 l/hr (USq/hr)	31.2 (8.2)
Fuel Consump, 165S l/hr (USq/hr)	33.5 (8.8)
Heat Rejected to Exhaust System: kW (Btu/min)	140.3 (7979)
Heat Rejected to Water & Lube Oil: kW (Btu/min)	72.9 (4146)
Heat Radiation to Room: kW (Btu/min)	42.9 (2440)
Exhaust Gas Temperature: °C (°F)	540 (1004)
Radiator Cooling Air Flow: m^3/min (cfm) Cooling system designed to operate in ambient conditions up to 50°C (122°F)	221.2 (7811)
Combustion Air Flow: m^3/min (cfm)	10.6 (374)
Exhaust Gas Flow: m^3/min (cfm)	29.9 (1056)

Dimensions and Weights

Length: mm (in)	**Width:** mm (in)	**Height:** mm (in)	**Dry:** kg (lb)	**Wet:** kg (lb)
2675 (105.3)	900 (35.4)	1564 (61.6)	1515 (3340)	1535 (3384)

Dry = With Lube Oil Wet = With Lube Oil and coolant

Ratings in accordance with ISO 8528. ISO 3046, IEC 60034, BSS5000 and NEMA MG-1/22
Generating set pictured may include optional accessories.

GENERAL ELECTROMAX COMPANY

11-KM, Jaranwala Road, Near Nazir CNG, Lahore - Pakistan.
Ph: +92-42-37902839-41 Fax : +92-42-37916484,
Email: info@gemco.com.pk web: www.gemco.com.pk

GEMCO

GEMCO150/165S